



**HIVE™**

# HIVE 433MHz Receiver

Stand Alone - Long Range DIP Switch Receiver



## FEATURES

- 2-Channels
- Maroon
- Includes Coax Antenna & Wiring Harness
- 12-24 VAC/DC
- 10 DIP Switches



## SPECIFICATIONS

|                        |                      |
|------------------------|----------------------|
| Output Load Max:       | 15A/125AC            |
| Input Load:            | 12-24VACDC           |
| Power Consumption:     | 32mA/70mA            |
| Max Applicable Power:  | 25VDC                |
| Operating temperature: | -40F - 158F          |
| Dimensions:            | 3W x 3 1/2L x 1 1/4D |
|                        |                      |
|                        |                      |
|                        |                      |
|                        |                      |

## ACCESSORIES

- Stinger 433MHz
- Firefly 433MHz



PIERCE BUILDING: 3788 WEST 2270 SOUTH, SUITE E  
 SALT LAKE CITY, UT 84120  
 (866) 975-0101 • (866) 975-0404 FAX  
 WWW.TRANSMITTERSOLUTIONS.COM

All items are trademarks of their respective holders.

To have your fax number removed from future specials, please call Removal Services - 800-915-2571 ext. 47540 or fax to 866-975-0404.